


COVERTTEL
 TELECOMMUNICATIONS GROUP

Need local support?

 Contact: Angelo Monteleone
 Email: angelo@covertel.com.au
 Mobile: +61 430 508 509 Office: 03 9381 7888
Get quick assistance without international delays.
Includes:

- Fiber Optic Power Meter
- Instruction Manual
- (3) AA Batteries (required for operation)
- (2) Cleaning Swabs
- FC Adapter
- SC Adapter
- FC-LC Adapter (Singlemode Only)
- Protective Carrying Case

Measures both the absolute optical power and relative power loss in fiber optic cables. Power measurement range (+10 ~ -70 dBm) with FC/SC/LC Adapters.

- Measures a wide variety of wavelengths
- Determines absolute or relative power
- Intelligent backlit control reduces power consumption
- Auto-off function can be turned on or off
- Automatic wavelength detection function
- FC, SC, & FC-LC adapters included
- Color LCD Display
- Backside Kickstand

SPECIFICATIONS	
DETECTOR TYPE	InGaAs
WAVELENGTH TEST RANGE (nm)	800 ~ 1700
MEASUREMENT RANGE (dBm)	+10 ~ -70
DEFAULT CALIBRATION WAVELENGTH (nm)	850/980/1300/1310/1490/1550/1625/1650
MINIMUM DISPLAY RESOLUTION (dB)	0.01
LINEARITY (dB) ¹	≤ 0.12
UNCERTAINTY	± 0.2
FREQUENCY IDENTIFICATION (Hz)	CW, 270 Hz, 330 Hz, 1000 Hz, 2000 Hz
MEASUREMENT UNIT	dBm, dB, xW
OPTICAL CONNECTOR	FC, SC
WAVELENGTH IDENTIFICATION ²	YES, USING OUR FLS-50 or FLS-55
DISPLAY SIZE	2.4-inch LCD
POWER SUPPLY	1.5V*3 AA ALKALINE BATTERIES
CONTINUOUS WORKING TIME ³	≥50 hr
AUTO TURN-OFF (min)	10
OPERATING TEMPERATURE (°C)	-10 ~ +60
STORAGE TEMPERATURE (°C)	-25 ~ +70
DIMENSIONS	7.44" x 3.31" x 1.85" (189 mm x 84 mm x 47 mm)
WEIGHT	0.64 lb (290 g)
UPC #	810053350478